

## MX-848



Mixer/preamplifier. Stereo and mono output. Suitable for P. A. and audio installations.

<b>INPUTS</b>	6 balanced mics./lines, combo (XLR and 6.3 mm jack), 1500 Ohm 7.7 mV y 10 000 Ohm 775 mV switchable 3 stereo auxiliaries, 2 x RCA, 10 000 Ohm 775 mV
<b>OUTPUTS</b>	1 balanced stereo master, XLR 120 Ohm 2.5 V maximum 1 balanced mono master, 6.3 mm jack, 120 Ohm 2.5 V maximum 1 balanced mono mix out, 120 Ohm 6.3 mm jack 1 line out, 2 x RCA 1000 Ohm 775 mV
<b>CONTROLS</b>	Tone: master output bass, mid and treble Volume: inputs 1 to 12 and general volume (stereo and mono master)
<b>RESPONSE</b>	10-20 000 Hz
<b>DISTORTION</b>	Harmonic: < 0.05% at 1 kHz
<b>S/N RATIO</b>	Microphones > 70 dB Auxiliary/Line > 103 dB
<b>PHANTOM</b>	18 V in mics. 1 to 6, selectable
<b>PRIORITY</b>	Mic. 1 depending on signal level, selectable
<b>POWER SUPPLY</b>	230 V AC, 18 W and 24 V DC, 500 mA
<b>DIMENSIONS</b>	483 x 44 x 220 mm depth. 1 U 19' rack
<b>WEIGHT</b>	3 kg

© 2017 Copyright by FONESTAR SISTEMAS, S.A.